



GTECH SOLAR LED Light

User Manual



- ① Expansion pillar-hinge
- ② Hole
- ③ Screw
- ④ Solar panel
- ⑤ PIR motion inductor
- ⑥ ON/Off Switch button
- ⑦ LED panel light

——.1.——

Specification:

1. Solar panel: 0.55w, 5.5V
2. Li-ion battery: 1200mAh, 3.7V
3. LED power: 0.2w, 5000K-5500K, 12PCS 22-24lm/Pcs
4. Motion angle and distance: 120°, 3m
5. Hight light delay: 10s
6. Switch: OFF/ON/AUTO MODES
7. Lighting mode functions:

Press once to enter motion sensor mode:

The light turns on when people are detected and the light turns off after people have left for 15s.

Press twice to enter motion sensor + low light mode:

The bright light is on when people are detected and then low light stays on after the people have left for 15s).

Press three times to enter low light mode:

The low light is on all of the time.

Press four times to turn off.

Product Features:

1. Recharged by sunlight and store power for overnight lighting.
2. Over 12 hours lighting time after one day of charging.
3. Weatherproof IP64, heatproof and durable.
4. Intelligent energy-saving.

——.2.——

Operating Instructions:

1. Unlock and activate the solar light:

The internal battery is locked from factory for safety shipment, so users have to use supplied Key pin to click the "on/off" switch hole and unlock the battery and lighting system.

2. How to install the device?

Please use the supplied Expansion pillar-hinge and screws to mount the device on a Pole or wall anywhere outside you want for lighting.

3. Charging via solar panel:

Please install the unit facing south and make sure the solar panel can get good sunlight directly without any shade or glass. Normally it can be fully charged in one day under ideal bright sunlight.

4. Motion sensor function


It will auto turn on the light when motion is detected within 2 meters and lasts 15s, then will auto turn off.

——.3.——


Working process instructions

The black button is the start switch
It's open, and then it's closed.

Then screw on the wall
by the supplied screws.




Step 1: Charging under sun in
day time around 7 hours




——.4.——

Step2: Auto bright light
at night when people
come close (lasts 15
seconds)



③

Step3: People move
away, light last 15s, then
auto turns off



——.5.——

Warning:

1. Keep the device away from fire and moist places in order to avoid explosion, leakage, moisture; (Weatherproof IP64).
2. Any severe shock to the charger is not recommended.
3. No one except professional technicians should attempt to disassemble the charger in order to avoid damaging the charger.

Tips:

1. Please fully charge the device before first use.
2. If there is no good sunlight in 3 months, the battery may be out of power, so you have to charge it by bright sunlight, when it's fully charged, please use Supplied Key Pin to unlock the device and lighting system, otherwise, it can't work anymore.
3. Mode: on/off, NO DIM MODE.

——.6.——

4. If the light is blinking, it means the power is very low, you have to charge it by sunlight soon. Otherwise, the device will stop working.
5. If there is no good sunlight or in winter sunlight, especially in North Countries, it may take a longer time to fully charge the device and this is normal for solar products.

Package included:

- 1 x Holan solar sensor light
- 1 X Expansion pillar-hinge
- 1 x Screw
- 1 x Manual

——.7.——